

Large Display Universal Mounting Bracket Kit


Installation Guide

DESCRIPTION

The Model MB6 Universal Mounting Bracket Kit provides the necessary hardware to mount the Large Display units in three configurations; suspended, horizontal surface mount, and vertical surface mount. The Kit consists of two brackets and hardware for the configurations shown. (*Vertical surface mounting requires two kits.*) The brackets are constructed of 14 ga. steel, and are finished with the same scratch resistant polyurethane paint as the Large Display units. The low profile design of the brackets keeps them from protruding beyond the Display's front panel. *Note: The panel gasket provided with the large display is not used with the mounting brackets*.

SUSPENDED MOUNTING PROCEDURE

Attach a screw eye bolt through the slot in each bracket as shown using two washers and two nuts. The display will hang level if the eye bolts are located on the line marked "CG" (center of gravity) on the bracket. Using the #10-32 kep nuts provided with the Large Display, attach the brackets to the studs on the Display's front panel as shown. The Display may now be hooked to any appropriate cabling. To tilt the Display forward, move the eye bolts to the rear of the slot; to tilt the Display backward, move the eye bolts to the front of the slot.






Figure 2


HORIZONTAL SURFACE MOUNTING PROCEDURE

Using the #10-32 kep nuts provided with the Large Display, attach the two brackets to the Display as shown. The threaded inserts in the brackets will now be 15 inches (38.1 cm) from center to center, and 2.65 inches (67.3 mm) from the front panel of the display. Using the dimensions given, mark and drill two 3/16" dia. holes in the surface. Install the #8-32 machine screws through the mounting surface and into the threads in the brackets. Mounting the Display on surfaces thicker than 3/16" (4.8 mm) will require longer machine screws than those provided in the kit.

Drawing No. LP0215 Revised 09 2021

VERTICAL SURFACE MOUNTING PROCEDURE

Vertical surface mounting requires two mounting kits. Each pair of brackets is bolted together by installing the # 8-32 machine screws through the slot of one bracket and into the threaded insert of the other. Attach the brackets to the Display by fastening them to the two studs on either end of the unit, with the #10-32 kep nuts provided with the Large Display. Position the unit on the panel and mark the mounting hole locations. Use #10 fasteners of a suitable type and length to fasten the Display to the surface. Drywall and other masonry products will require toggle bolts or anchors, thin sheet metal panels may require bolts and nuts, heavier gage panels may be drilled for self tapping screws or drilled and tapped for machine screws.



| MODEL NO. | DESCRIPTION | PART NUMBER |
|-----------|-------------------|-------------|
| MB6 | Mounting Brackets | MB600000 |

COPYRIGHT

©2021 Red Lion Controls, Inc. All rights reserved. Red Lion and the Red Lion logo are trademarks of Red Lion Controls, Inc. All other company and product names are trademarks of their respective owners.

RED LION CONTROLS TECHNICAL SUPPORT

If for any reason you have trouble operating, connecting, or simply have questions concerning your new product, contact Red Lion's technical support.

Support: support.redlion.net
Website: www.redlion.net
Inside US: +1 (877) 432-9908
Outside US: +1 (717) 767-6511

Red Lion Controls, Inc.

20 Willow Springs Circle York, PA 17406

LIMITED WARRANTY

(a) Red Lion Controls Inc. (the "Company") warrants that all Products shall be free from defects in material and workmanship under normal use for the period of time provided in "Statement of Warranty Periods" (available at www.redlion.net) current at the time of shipment of the Products (the "Warranty Period"). EXCEPT FOR THE ABOVE-STATED WARRANTY, COMPANY MAKES NO WARRANTY WHATSOEVER WITH RESPECT TO THE PRODUCTS, INCLUDING ANY (A) WARRANTY OF MERCHANTABILITY; (B) WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE; OR (C) WARRANTY AGAINST INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHTS OF A THIRD PARTY; WHETHER EXPRESS OR IMPLIED BY LAW, COURSE OF DEALING, COURSE OF PERFORMANCE, USAGE OF TRADE OR OTHERWISE. Customer shall be responsible for determining that a Product is suitable for Customer's use and that such use complies with any applicable local, state or federal law. (b) The Company shall not be liable for a breach of the warranty set forth in paragraph (a) if (i) the defect is a result of Customer's failure to store, install, commission or maintain the Product according to specifications; (ii) Customer alters or repairs such Product without the prior written consent of Company.

(c) Subject to paragraph (b), with respect to any such Product during the Warranty Period, Company shall, in its sole discretion, either (i) repair or replace the Product; or (ii) credit or refund the price of Product provided that, if Company so requests, Customer shall, at Company's expense, return such Product to Company.

(d) THE REMEDIES SET FORTH IN PARAGRAPH (c) SHALL BE THE CUSTOMER'S SOLE AND EXCLUSIVE REMEDY AND COMPANY'S ENTIRE LIABILITY FOR ANY BREACH OF THE LIMITED WARRANTY SET FORTH IN PARAGRAPH (a).

BY INSTALLING THIS PRODUCT, YOU AGREE TO THE TERMS OF THIS WARRANTY, AS WELL AS ALL OTHER DISCLAIMERS AND WARRANTIES IN THIS DOCUMENT.

